

ROP-401/EU

ADDRESSABLE MANUAL CALL POINT FOR OUTDOOR USE

The **ROP–400** call point for outdoor applications is used to manually trigger an alarm when a fire is discovered. It is designed to operate in the detection line of the **ACSP–402**; addressable fire alarm control panel.

- resettable plastic pane
- ROP-KEY-U key (sold in set) to enable:
- testing
- resetting

LED indicator/li>

double–sided short–circuit isolator power supply from the detection line mounting box included optional protective cover to prevent unintentional activation – ROP–FLAP



TECHNICAL DATA

Operating temperature range	-25°C+70°C
Weight	180 g
Maximum humidity	95%
Current draw when detecting	170 μΑ
Current draw when emitting an alarm	450 µA
IP rating	IP66
Power supply voltage	1826 V DC
Dimensions without holders	87 x 87 x 53 mm
Dimensions with holders	117 x 87 x 53 mm

