

PB-10

PANIC BUTTON

PB-10 is a wired panic button used to trigger a panic alarm or call for help. The button can also be used to control various devices (e.g. automation or access control system devices).

- tamper protection against opening the enclosure and detaching it from its mounting surface
- compatible with any alarm control panels that supports NC type detectors



TECHNICAL DATA

Operating temperature range	-10°C...+55°C
Weight	58 g
Maximum humidity	93±3%
Dimensions	ø97 x 29 mm
Environmental class according to EN50130-5	II
Tamper outputs (NC)	10 mA / 24 V DC
Alarm outputs (NC)	100 mA / 24 V DC