

## ANT-900/1800

## **GSM ANTENNA**

The ANT–900/1800 dual–band antenna is designed to work in conjunction with the **GSM–4**, **GSM LT–1**, **GSM LT–2**, **GPRS–T1**, **GPRS–T2**, **GPRS–T4**, **GPRS–T6** modules as well as the **INTEGRA 128–WRL** control panel. The antenna comes with a standard SMA connector, so it can be also used in other devices provided with such a connector. The cable with a length of 2,5 meters and a magnetic base are used for easy mounting, even at some distance from the interacting device. This allows positioning of the antenna in a location with optimal GSM signal strength.

The antenna works in the following frequency bands: 900/1800 MHz.

 900/1800MHz antenna for GSM-4, GSM LT-1, GSM LT-2, GPRS-T1, GPRS-T2, GPRS-T4, GPRS-T6, INTEGRA 128-WRL modules



## **TECHNICAL DATA**

Operating frequency	900/1800 MHz
Cable length	2.5 mm
Impedance	50 Ohm
Cable	kabel koncentryczny RG174 (czarny)
VSWR	<2.0
Operating temperature range	-20+60°C
Connector	SMA